

## Mobile power for trucks, RVs, and boats

Available in:

**400 W**



Designed to power electronics while on the go, our new compact digital inverters combine innovative industrial design with an advanced interactive LED display. This provides the user with instant feedback on input current and output voltage, and valuable troubleshooting guidance through Fault Codes. These new digital inverters provide a convenient and powerful way to access AC power.

### XPower Digital 400

- » 320 watts continuous power with 640 watts surge
- » Automatic shutdown protection against overload, over temperature and low/high battery conditions
- » DC terminals for a lighter socket or direct battery connection
- » Two, three-prong grounded AC outlets
- » 12 month warranty
- » Runs cell phone, camcorder, stereo, laptop computer, 20" TV/VCR combo, 27" TV

### Applications:



Recreational  
vehicles



Marine



Work  
vehicles



Electrical specifications	400
Continuous AC output power	320 W
5 minutes AC output power	400 W
Maximum AC output surge power	700 W
AC output voltage (nominal)	115 VAC
AC output frequency	60 +/- 1 Hz
AC output waveform	Modified sine wave
Battery drain with no AC load (at 12V input)	0.25 A
Efficiency (maximum)	90%
DC input voltage range	10.5-15.5 VDC
Low battery alarm trigger point (nominal)	11.0 V
Low battery shut down point (nominal)	10.5 V
High battery shut down point (nominal)	15.5 V

General specifications	
Ambient operating temperature range	0°C-40°C (32°F-104°F)
Dimensions (H x W x L)	9.25 x 3.64 x 6.68" (235x 92.68 x 169.72 mm)
Weight	2.2 lb (0.99 kg)
Warranty	12 months
DC connection	DC plug and battery clips
Part Number	813-0400-01

Packaging specifications	
Retail package size (H x W x L)	9.0 x 6.5 x 3.8" (228.0 x 165.1 x 96.5 mm)
Weight	2.4 lbs (1.0 kg)

Specifications are subject to change without notice. \*Selectable range.