

MNLR3648M Inverter/Charger

The new Little Rosie Inverter/Charger is an exciting addition to the family of MidNite Solar Inverters!

PRODUCT FEATURES

- True sinewave inverter with charger
- 60-amp charger
- Aux input/outputs
- Listings: UL458 and CSA
- Powder-coated aluminum enclosure
- Auto Gen Start (2-wire generators)
- MidNite BTS Optional
- Quiet forced air cooling over heat-sink fins and transformer compartment
- Canbus communications
- Light-weight: 15 lbs.
- Built in Arlington, WA USA
- 5 year warranty



PRODUCT SPECIFICATIONS

AC Output Voltage (Accuracy)	120VAC ($\pm 2\%$)
AC Input Frequency Range	48 to 72 Hz
Output Power (Continuous @40°C)	3600W
Input Battery Voltage Range	40 to 63 VDC
Power Factor Corrected Charging	Yes
Grid/Generator Support	Yes
5 Second Surge	>5400W
Battery Charge Profiles	Lithium/Custom
AC Pass-thru Capacity	30 AAC
AC Input Voltage Limits	82 to 140 VAC

Made in the USA

