



**Inverter  
Remote  
Control**

Model  
RC-300

### Design Features

- LCD displays AC Volts, AC Amps, frequency, power (watts), and power factor
- LED Indicators for overload, over temperature and power
- Includes 25' cable
- Sold separately

Optional wired remote control for use with PST Series 1500-3000W inverter models.

## 3 YEAR LIMITED WARRANTY

		MODEL NO.	RC-300
COMPATIBLE INVERTERS	MODEL NUMBERS	PST-1500-12, PST-1500-24, PST-1500-48 PST-2000-12, PST-2000-24 PST-3000-12, PST-3000-24 PST-300S-12E, PST-300S-24E	
DISPLAY	LCD DISPLAY	AC Voltage (V), AC Current (A), Frequency (Hz), Active Power (Watts), Apparent Power (VA) and Power Factor (PF)	
	LED INDICATORS	Overload, Over Temperature and Power	
INPUT / OUTPUT CONNECTION	CABLE SET	RJ-50 (10p10C) with crossed-over / rolled-over connections Length: 7.6 Metres / 25 Feet. Ferrite core installed at one end (inverter end) of the cable set.	
ENVIRONMENT	OPERATING TEMPERATURE RANGE	0°C to 40°C / 32°F to 104°F	
DIMENSIONS	(W X H X D), MM	110 x 65 x 24.7	
	(W X H X D), INCHES	4.33 x 2.56 x 0.97	
WEIGHT	WEIGHT WITHOUT CABLE	85 g / 0.04 lbs	

NOTE: Specifications are subject to change without notice